



SFC1450A

Ku-Band Synthesized Frequency Upconverter



HIGHLIGHTS

- ▶ Low-Cost and High Performance in a 1.75" High Chassis
- ▶ Built-In 1:N Series Switching Option
- ▶ +23 dBm Output Intercept Drives 200 Extra Feet of Coaxial Cable
- ▶ 50 dB of Gain Control at 0.1 dB Resolution
- ▶ Versatile Input and Output Attenuator
- ▶ -80 dBc Spurious Suited for Large Earth Stations
- ▶ 125 kHz Frequency Resolution
- ▶ Low Phase Noise
- ▶ Low Group Delay Distortion for High Data Rates and DVB

OVERVIEW

The Radyne Model SFC1450A Ku-Band Synthesized Frequency Upconverter has been designed to provide performance that meets or exceeds industry standards. The SFC1450A features also provide ease of integration and operation.

The SFC1450A offers the highest standard output power of any rack-mount upconverter available. With an output P1 dB in excess of +10 dBm, the SFC1450A may eliminate the need for line amplifiers in your next installation. Installation of the SFC1450A into any existing earth station is easily accomplished due to the presence of independently adjustable input and output attenuators that provide total gain control of 50 dB. The input attenuator optimizes the existing IF power applied to the converter to a level which guarantees optimal performance over 30 dB of input signal power. Output power is adjustable over 20 dB which further guarantees that spurious performance is maintained independently of upconverter gain.

Linearity of the converter is equally impressive. The SFC1450A boasts a two tone IMD products of -46 dBc for a combined output power of 0 dBm. Phase linearity is maintained through an internal group delay equalizer that limits parabolic plus linear group delay to less than three nanoseconds across the band. Thus, the SFC1450A is ideally suited for multiple carrier or DVB uplinks where linearity and group delay distortion becomes critical.

MONITOR AND CONTROL

All of the configuration, monitor and control functions are available at the front panel. Operating parameters such as frequency, channel, gain, gain offset and switch settings (backup only) can be readily set and changed at the front panel.

Additionally, all functions can be accessed with a terminal or personal computer via a serial link (RS-232, RS-485, or Ethernet) for complete remote monitor and control (M&C) capabilities.

Extensive fault monitoring with masking capability, along with time and date stamped event storage are available.

PROTECTION SWITCH VERSATILITY

Redundancy for the SFC converter products can be supported by a built in Series Switch or by an external rack mounted RCU101 (1:1) or RCU108 (1:N) system. These redundant systems are designed to ensure continuous operation thus allowing a unit to be replaced without disruption of the signal transmission. The Radyne 's built in Series Switching can be configured from a 1:1 to 1:8 redundant system without the need for additional hardware or support equipment. In either case, the built in Series Switch, RCU101 or the RCU108 can be easily configured by connecting the cables and starting the plug and play process.

Identical firmware enables any converter to be plugged into the backup slot and assume the role of protection switch controller. It is the backup converter that learns and stores the frequency, gain and channel settings of the primary converters. The backup converter can be operated automatically, in which case an automatic backup of a failed on-line converter occurs after a user pre-programmed delay. The backup may also be operated manually, allowing the operator to manually switch-in the backup unit.

In the event the stored setting of the primary converter is changed, the backup converter will notify the user.

Switching configuration settings, such as priority, fault delay, force and learn controls, backup testing, and compensation, are available on the front panel and all serial interfaces. Status information on all primes, such as summary fault, learn and backup status tests, configuration change, relay status, and converter type, is also available.

All circuits are protected upon installation of the switch and upon completion of the learning process. This eliminates the need for complicated software configurations that might otherwise leave a circuit vulnerable. Likewise, replacing a failed converter is as simple as plugging in a replacement.



SFC1450A Ku-Band Synthesized Frequency Upconverter

SPECIFICATIONS

OUTPUT CHARACTERISTICS

Frequency:	14.00 to 14.50 GHz Standard 13.75 to 14.50 GHz Extended
Impedance:	50 Ohms
Return Loss:	≥19 dB
P1 dBm Output:	+10 dBm Minimum
Output Attenuation:	0 to 20 dB Continuously in 0.1 dB Steps
Connector:	SMA, Type-F

INPUT CHARACTERISTICS

Frequency:	70 MHz ±18 MHz Standard 140 MHz ±36 MHz Optional
Impedance:	75 Ohms
Return Loss:	≥23 dB
P1 dBm Input:	+10 dBm (Input Attenuator @ 30 dB) -15 dBm (Input Attenuator @ 0 dB)
Pin Nominal:	+5 dBm (Input Attenuator @ 30 dB) -25 dBm (Input Attenuator @ 0 dB)
Connector:	BNC F

TRANSFER CHARACTERISTICS

Type:	Double Conversion, No Spectral Inversion
Gain:	30 dB Maximum @ 0 dB Total Attenuation
Gain control:	50 dB in 0.1 dB Increments (30 dB to -20 dB Conversion Gain)
Gain Ripple:	±0.50 dB/36 MHz Typical, ±0.75 dB Maximum
Gain Slope:	±0.05 dB/MHz
Gain Stability:	±0.25 dB/24 Hours, ± 1.0 dB; 0 to 50°C
Spurious:	-80 dBm Local Oscillator Related Spurious (In-Band) at Maximum gain -60 dBc Signal Related Spurious (In-Band) at Minimum Attenuation
Third Order Intercept:	+23 dBm -46 dBc IMD Two Tones with +0 dBm Total Output Power
AM/PM Conversion:	0.15°/dB @ +5 dBm Output

GROUP DELAY

Linear:	0.025 nsec/MHz
Parabolic:	0.005 nsec/MHz ²
Ripple:	1 nsec p-p
Carrier Mute:	80 dB Minimum

FREQUENCY SYNTHESIZER CHARACTERISTICS

Resolution:	125 kHz Step Size
Accuracy:	±5 x 10 ⁻⁹
Stability:	±5 x 10 ⁻⁹ Over Temperature (0 to 50°C) ± 1 x 10 ⁻⁹ /24 Hours
Accuracy:	±5 x 10 ⁻⁹

SINGLE SIDE BAND PHASE NOISE

Offset	<u>Ku-Band Standard</u>
10 Hz	-50 dBc/Hz
100 Hz	-60 dBc/Hz
1 KHz	-80 dBc/Hz
10 KHz	-84 dBc/Hz
100 KHz	-94 dBc/Hz
1 MHz	-110 dBc/Hz
External Reference	10 MHz, 0 dBm, 50 Ohms (5 MHz Optional)

OPERATOR INTERFACE

Front Panel:	Keypad Control, LED Indicators, and LCD Indicators
--------------	---

Remote Interfaces:	Terminal (RS-232), ASCII and RLLP (RS-232/RS-485) Serial Interfaces, and SNMP (Ethernet) 10Base-T
Rear Panel Connections:	RF Output (SMA-F), IF Input (75 Ohm BNC), Operator Serial Port (DB-9 Pin), 10 MHz REF In (50 Ohm BNC), 10 MHz REF Out (50 Ohm BNC), Fault/Test (DB-9 Pin), Switch Interface (DB-15 Pin), Equipment RS-485 Interface (DB-9 Pin), IEC/EN60320/C13 Power Entry Module/Switch, #10 Ground Lug, Series Switch Interface (Option)
Front Panel Test Ports:	RF Monitor -15 dB (Nominal) SMA-F, IF Monitor -15 dB SMA-F
Converter Settings:	Monitored and/or controlled from the front panel or remotely, using the RS-232/RS-484 or Ethernet remote port:

- Frequency
- Current Channel
- Event Buffer
- Power Supply Voltages
- Input Attenuation
- Carrier Control and Status
- Converter and Frequency Type
- Terminal Emulation and Baud Rate
- Channel Gain
- Gain Offset
- Faults Status and Mask
- Frequency Reference Status and Offset Control
- Remote Protocol, Baud, Line, and Echo Modes
- Converter Band and User Minimum/Maximum Frequencies
- RF Detector, IF Detector, and DAC Attenuation Voltages

Switch Settings:	Monitored and/or controlled from the front panel or remotely, using the RS-232/RS-484 or Ethernet remote port (backup only):
------------------	--

- Priority
- Fault Delay
- Force Backup
- Learn Control
- Backup Testing
- Compensation Control
- All Available Prime Summary Fault
- All Available Prime Learn Status
- All Available Prime Backup Test Status
- All Available Prime Configuration Change Status
- All Available Prime Relay Status
- All Available Prime Converter Types

LED Indications:	Standby, LO Fault, Sig Fault, Ext Ref Online, Backup, SwFault, Manual (Backup Only), Power, Fault, Event, Remote
------------------	--

PHYSICAL CHARACTERISTICS

Size:	19" x 21" x 1.75" (48.26 cm x 53.34 cm x 4.44cm)
Weight:	12 Pounds (5.44 kg)
Primary Power:	100 to 240 VAC, 50 to 60 Hz
Power Consumption:	50 Watts

ENVIRONMENTAL CHARACTERISTICS

Operating Temperature:	0 to 50°C
Humidity:	To 95% non-condensing
Altitude:	To 8,000 Feet (2438.4 meters) AMSL
Shock & Vibration:	No loss of frame synchronization at the BER Test set due to a standard hammer drop test on any outside surface of converter. Likewise, no loss of frame sync for temperature gradient of ±22°C/hour

Non-Operating Temperature:	-32 to +70°C, 99% Humidity, Non-Condensing
----------------------------	--

U.S.A./Canada: 3138 East Elwood Street, Phoenix, Arizona 85034 USA, Tel: +(1) 602.437.9620 Fax: +(1) 602.437.4811
7330 Trade Street, San Diego, California 92121 USA, Tel: +(1) 858.805-7000 Fax: +(1) 858.805-7001

Europe/Middle East/Africa: 13 The Enterprise Centre, Coxbridge Business Park, Farnham, Surrey, GU10 5EH, United Kingdom
Tel: +(44) 1420.540.233 Fax: +(44) 1420.540.232

Latin America: 3138 East Elwood Street, Phoenix, Arizona 85034 USA Tel: +(1) 561.487.7972 Fax: +(1) 561.892.2363
China: Room 405, Building B, Heqiao Mansion, No. 8 Guanghua Road, Chaoyang District, Beijing 100026 China,
Tel: +(86) 10.658.31975 Fax: +(86) 10.658.31974

Asia-Pacific: 150 Cecil Street, #08-02, Singapore 069543 Tel: +(65) 6325.1956 Fax: +(65) 6325.1950
Wisma Budi, 7th Floor Suite 702, J1. H.R. Rasuna Said Kav. C6, Jakarta 12940 Indonesia, Tel: +(62) 21.252.2676 Fax: +(62) 21.252.0142

www.radn.com

Prices, specifications, and product availability subject to change without notice. All trademarks acknowledged.

© Copyright 2007 Radyne Corporation. All rights reserved.

ML-0403C 06-28-2007

