hubmount SSPA 80 W to 125 W U B A D



INTRODUCTION

Ku-BAND HUBMOUNT SSPA with basic control

Medium Power 80 W to 125 W

AWSA-K80; AWSA-K100; AWSA-K125 The AWMA-K series described in this section are for Advantech's line of high power solid state power amplifiers (SSPAs) with basic control and output power ranging from 80 watts to 125 watts. Other Ku-band hubmount SSPAs are available for output powers from 2 watts to 1000 watts.

Advantech's hubmount SSPAs are designed for outdoor operation in hard environmental conditions and are particularly suited to flyaway or mobile applications as SNG, where efficiency and size considerations are critical. Advantech's hubmount SSPAs set the industry standard for operating efficiency and feature compact and lightweight construction.

STANDARD FEATURES

- High gain, linearity and efficiency
- Gain control (local)
- Remote RF mute capability
- Temperature gain compensation
- Automatic over-temperature shutdown
- Automatic high reflected power shutdown
- Output sample monitor ports
- Form-C contacts for fault/alarm conditions
- Infinite VSWR protection
- CE Marking

OPTIONS

- Extreme temperature operation
- Power factor correction



ADVANTECH, Advanced Microwave Technologies, Inc. 657 Orly Avenue, Dorval, PQ H9P 1G1 Tel. (514) 420-0045 Fax (514) 420-0073 sales@advantech.ca www.advantech.ca

TECHNICAL SPECIFICATIONS			80 W	100 W	125 W
			Electrical Charac	eteristics	
Frequency	ranges		14.00 – 14.50 GHz (KS series); 13.75 – 14.50 GHz (KX series); 15.45 – 15.65 GHz (KH series); 14.87 – 15.13 GHz (CX series)		
Saturated output power nominal			+49 dBm	+50 dBm	+51 dBm
Output power (P1dB)			+48 dBm	+49 dBm	+50 dBm
Gain minimum ($G_{max} = G_{min} + 5 dB$)			58 dB	59 dB	60 dB
Gain flatness over 600 MHz		±1 dB max.			
Gain slope		0.6 dB/40 MHz max.			
Gain variation		±1.5 dB max.			
Gain adjustment range			20 dB min.		
Input VSWR			1.3:1 max.		
Output VSWR			1.25:1 max.		
Noise Figure			10 dB at max. gain		
Spurious at rated power			-65 dBc, max.		
Harmonics at rated power			-65 dBc, max		
AM/PM conversion at rated power		2.5°/dB max. at P1dB, 1°/dB max. at 3 dB back-off			
Two tone intermodulation (5 MHz apart)		-33 dBc min. at 7 dB total back-off from rated P1dB, -25 dBc min. at 3 dB total back-off from rated P1dB			
Group Delay		Linear: 0.02 dB/MHz max. Parabolic: 0.003 dB/MHz ² max.			
Phase Noise		Ripple 1 nsec p-p max. Meets IESS-308/309			
Residual AM			0-10 kHz	-45 dBc	
(F* - frequency in kHz)		10 kHz - 500 kHz			
			Power Require	ments	
Operating voltage			220 VAC (47 -63 Hz)		
Power consumption, nominal		1200 W	1550 W	1800 W	
			Mechanical Chara	cteristics	
Dimentions (W x H x L)		16" x 13.5" x 31"			
Weight		50 kg (110 lbs)			
Interfaces	RF input		Type-N female		
	Output sample port		Type-N female		
	RF output		WR-75 cover		
	Discrete port		MS3112E16-26P		
	Power		MS3102E20-19P		
			Environmental Co	onditions	
Temperature St		perating	-30°C to +55°C option 2: -40°C to +55°C option 3: -50°C to +55°C -55°C to +85°C		
		torage			
Humidity		100% condensing, up to 2"/hour rain			
Altitude			10,000' AMSL, derated by 2°C/1000' from AMSL		

All our specifications are guaranteed over full specified temperature range.



hubmount SSPA 80 W to 125 W KU-BAND



